	Dhamat Dillag I 4.1			Customer				
Manufacturer Type of motor	Bharat Bijlee Ltd.3 phase Induction Motor			Customer BBL Enquiry reference No				
Quantity	5 phase multion wrotor			BBL Enquiry reference No Customer P.O.Number				
Application	on CUSTOMER TO FURNISH		W.O. No. / SAP No.					
Fag no.			Output kW / Pole	37 / 2P				
BBL type Ref.		MD20L253		Frame size	57	 MJ200		
Installation detail	ils	NID 2012233		Applicable standards (latest edition)		1115200		
		Hazardous area		Performance: IS/IEC 60034-1 Maintenance IS:900	FLP Mote	ors · IS/IEC	60079-	
Area classification (Safe / Hazardous) Location: indoor/outdoor/deck		Indoor	u	Dimensions: IS 1231/IS 2223/IS:8223	0 FLP Motors: IS/IEC 6007		00077	
Altitude (meters)				Vibrations: IS 12075				
Intitude (Interes)				Noise level: IS 12075				
Hazardous area	details			Supply conditions and permissible variations (grid	l supply)			
Area classification GAS (Zone 1/Zone 2)				Number of phases			Three	
Gas group		IIA, IIB		Voltage (Volts) and permisible variation	415 ±10%		0%	
Temp.class				Frequency (Hz) and permissible variation	$50 \pm 5\%$			
Type of Explosion protection				Combined variation (absolute sum)	±10%			
(EL D/Type 'e'/Type 'e') Approving authority for hazardous area		If Mine application then DGMS   else PESO						
Electrical param								
Starting perform								
Method of startin	0	DOL		Starting current (%FLC)	650			
Load speed (rpm)	-	CUSTOMER TO FU	RNISH	Starting torque (%FLT)	250			
Motor $GD^2$ (kgm <sup>2</sup> )		0.61		Pull out torque (%FLT)	250			
Load $GD^2$ (kgm <sup>2</sup>	2)	CUSTOMER TO FU	RNISH	Locked rotor withstand time (hot/cold) (sec)	12 / 24		24	
Load torque-speed curve		Parabolic IS curve		Number of consecutive starts (hot/cold) (nos.) provided Load GD2 = Motor GD2	2/3			
Starting time at ra	ated voltage (sec)	PLEASE FURNISH AL DETAILS	L ABOVE					
<b>Running Perform</b>	nance							
Efficiency class		_		Duty and designation	Continuous (S1)			
Ambient temp./temp.rise by resistance (deg.C)		45 / 75		CDF/Equivalent starts per hour/FI				
Enclosure		TEFC (TOTALLY ENCLOSED FAN COOLED)		Insulation class / utilisation class on DOL	F/B			
Full load current (FLC) amps.		62.9		Rotor type (Squirrel Cage/ Slip ring )	Squirrel Cage			
Full load speed (rpm)		2945		Rotor voltage/rotor current (RV/RA) (Volts/Amps)	Not applicable			
Full load torque (FLT) kg-m		12.2		Stator/rotor time constant (min)	144/194			
Efficiency in % a	t FL/0.75FL/0.5FL	93.0 92.5	91.0	Power factor at FL/0.75FL/0.5FL	0.88	0.85	0.79	
Mechanical para	imeters				-			
Mounting		B3		Mounting dimensions	Re	efer GA dra	wing	
Shaft extention		Single cylindrical		Direction of rotation viewed from DE	Clockwise			
Degree of protect	tion	IP 55		Suitable for bidirectional rotation	Yes			
Method of cooling (TEFC/forced cooled/TESC)		TEFC (IC 411)		Paint type	Acid Alkali Proof			
Net weight of mo	otor (kg)	320		Paint shade	(	532 as per I	S 5	
Bearings				Earthing provision (two terminals on stator body) <i>Terminal box</i>		Yes		
Coupling (Direct/flexible/Belt & Pulley/Gearbox)		Direct		Terminal box location when viewed from DE	As per GA drawing			
Dimenssions of pulley (OD x width) mm		-		Direction of cable entry	As per GA drawing			
Bearings (roller/ball/angular contact)		Ball /Ball		Cable size and type(Aluminium)	2R X 3C X 50 SQ MM			
Bearing size DE/NDE		6212 2Z C3/6212 2Z C3		Earthing provision (one terminal in TB)	Yes			
Type of lubrication	on	LITHIUM SOAP BASE	GREASE	tomainala		3 / DELTA	/ 6	
Accessories	•							
	rs simplex(w/o controller)			Arrow plate for direction of rotation				
BTDs - 1 number per bearing(w/o controller) Space heaters - single phase 50z, 230V				Double compression glands (main cable) Double compression glands (Space				
•				heater/Thermisters/RTDs)				
Thermisters - PT	С			Brake (Type/voltage/torque)				
Thermisters - P I								
Additional T-Box	x for Accessories							

2) Performance values are at rated voltage and rated frequency condition and for DOL starting condition.

3) Motor  $GD^2 = Load GD^2$  assumed wherever not mentioned.

4) Where starting time is more than 10 seconds, provision of heavy duty relays is mandatory.

5) Kilowatt rating is mandatory and HP is approximate.

6) Accessories provided are marked as "YES"

Prepared by	
Approved by	

			Revison	
<b>Project:</b>	Contractor/Client		Date:	
Consultant	Package			