Bharat						
Manufacturer	Bharat Bijlee Ltd.		Customer			
Type of motor	3 phase Induction Motor		BBL Enquiry reference No			
Quantity	CUSTOME		Customer P.O.Number			
Application	CUSIOME	CR TO FURNISH	W.O. No. / SAP No.	15	1	οn
Tag no. PBL type Dof		MD28M853	Output kW / Pole Frame size	45	/ MJ280	8P
BBL type Ref.	ile	WID20W1033	Applicable standards (latest edition)		WIJ200	
	on (Safe / Hazardous)	Hazardous area	Performance: IS/IEC 60034-1 Maintenance IS:900	FI P Mot	ors: IS/IEC 6	50079_1
Location: indoor/	· · · · · · · · · · · · · · · · · · ·	Indoor	Dimensions: IS 1231/IS 2223/IS:8223		JIS. 15/11/C (50079-
Altitude (meters)		1000 or less	Vibrations: IS 12075			
Antitude (meters)			Noise level: IS 12075			
Hazardous area	details		Supply conditions and permissible variations (grid	sunnly)		
•	on GAS (Zone 1/Zone 2)	ZONE I	Number of phases		Three	
Gas group		IIA, IIB	Voltage (Volts) and permisible variation	415	±10)%
Temp.class		T4	Frequency (Hz) and permissible variation	50	±59	
rypé or Explosio		Ex 'd'	Combined variation (absolute sum)	50	±10%	/0
Approving author	rity for hazardous area	If Mine application then DGMS else PESO			21070	
Electrical param						
Starting perform				1		
Method of startin	0	DOL CUSTOMED TO FUDNICU	Starting current (%FLC)	550		
Load speed (rpm)	, _	CUSTOMER TO FURNISH	Starting torque (%FLT)	220		
Motor GD^2 (kgm		6.86	Pull out torque (%FLT)	 	220	
Load GD ² (kgm ²	2)	CUSTOMER TO FURNISH	Locked rotor withstand time (hot/cold) (sec)	15	/	30
Load torque-speed curve		Parabolic TS curve	Number of consecutive starts (hot/cold) (nos.) provided Load GD2 = Motor GD2	2/3		
Starting time at ra	ated voltage (sec)	PLEASE FURNISH ALL ABOVE DETAILS				
Running Perform	mance			_		
Efficiency class		_	Duty and designation	C	continuous (S1)
Ambient temp./te	emp.rise by resistance (deg.C)	45 / 75	CDF/Equivalent starts per hour/FI		-	
Enclosure		TEFC (TOTALLY ENCLOSED FAN COOLED)	Insulation class / utilisation class on DOL		F/B	
Full load current	(FLC) amps.	86.1	Rotor type (Squirrel Cage/ Slip ring)		Squirrel Cag	ge
Full load speed (rpm)		730	Rotor voltage/rotor current (RV/RA) (Volts/Amps)	Not applicable		ole
Full load torque ((FLT) kg-m	60	Stator/rotor time constant (min)		144/194	
Efficiency in % a	t FL/0.75FL/0.5FL	92.0 92.0 91.0	Power factor at FL/0.75FL/0.5FL	0.79	0.75	0.65
Mechanical para	ameters					
Iounting		B3	Mounting dimensions	Refer GA drawing		ving
Shaft extention		Single cylindrical	Direction of rotation viewed from DE	Clockwise		;
Degree of protect	tion	IP 55	Suitable for bidirectional rotation	Yes		
Method of cooling (TEFC/forced cooled/TESC)		TEFC (IC 411)	Paint type	Acid Alkali Proof		roof
Net weight of motor (kg)		725	Paint shade Earthing provision (two terminals on stator body)	632 as per IS 5 Yes		
Bearings			<i>Terminal box</i>	<u> </u>		
Coupling (Direct/ Pulley/Gearbox)	/flexible/Belt &	Direct	Terminal box location when viewed from DE	As per GA drawing		
•	oulley (OD x width) mm		Direction of cable entry	Δα	per GA dray	wing
Ĩ	ball/angular contact)	- Ball /Ball	Cable size and type(Aluminium)	As per GA drawing 2R X 3C X 120 SQ MI		
Bearing size DE/	NDF	6317 C3/6316 C3	Earthing provision (one terminal in TB)			
<u> </u>		SKF LGMT3- GREASE	Earthing provision (one terminal in TB)	Yes 3 / DELTA / 6		
Type of lubrication		SKT LUNITS- UKEASE	tampinala		J/ DELIA/	U
Accessories	re simplay (m/a aantrallar)		Arrow plata for direction of rotation			
	rs simplex(w/o controller)		Arrow plate for direction of rotation			
	r per bearing(w/o controller)		Double compression glands (main cable)			
Space heaters - si	ingle phase 50z, 230V		Double compression glands (Space			
Thomas Dr.	$\overline{\mathbf{C}}$		heater/Thermisters/RTDs)			
			Drake (Type/vollage/torque)			
Additional namer						
Thermisters - PT Additional T-Box Additional name <i>Notes:</i>	x for Accessories plate	60024.1 toloron and unloss otherwise	Brake (Type/voltage/torque)			

1) All performance values are subject to IS/IEC 60034-1 tolerances, unless otherwise specified.

2) Performance values are at rated voltage and rated frequency condition and for DOL starting condition.

3) Motor $GD^2 = Load GD^2$ assumed wherever not mentioned.

4) Where starting time is more than 10 seconds, provision of heavy duty relays is mandatory.

5) Kilowatt rating is mandatory and HP is approximate.

6) Accessories provided are marked as "YES"

Prepared by	
Approved by	

		Revison	
Project:	Contractor/Client	Deter	
Consultant	Package	Date:	